

Second Floor Laser Printer Setup PC Version

Leitman

Compiled July 1, 1999, 11h:55m

Follow these steps

1. Sign out the CD-Rom for Diane
2. Close all programs (restarting your computer is better)
3. Insert CD-Rom, open its root directory, double click on **Setup.exe**
4. Click **Next** in the “Welcome” window that appears.
5. **Accept** the license agreement.
6. In the next dialog window, if you are connected to the network, **Check** the box to “Perform Internet Install.” Click **Next** (This will load all relevant new drivers and other stuff. It takes a few minutes.)
7. In the next dialog box select the radio button for **Custom**. Click **Next**.
8. **Select** 4050N. Click **Next**.
9. **Select** the radio button for **Connected Directly to a Network**. Click **Next**.
10. Click **Create Port**. Click **OK** in Additional Components Box. Click **Next**.
11. You will be prompted to select components. **Highlight** PCL 6 Drivers. Click **Options**. **Select** bidirectional option. Click **OK**.

12. Now select the HP LaserJet 4050N PCL 5E driver. Click **Options**. **Select** bidirectional option. Click **OK**. Click **Next**. (The program will now go to get files from the network. This may take a few minutes. If you get a “Fonts already loaded” message, click **OK**.)
13. You can read the “Read Me” file if you wish.
14. Click **Restart**. (This will restart as usual but will end up back in the Setup program.)
15. In the dialog box that appears, **select** the radio button for “Easy” install. Click **Next** to launch the Wizard.
16. **Select** the radio button for TCP/IP Printer. In the box for Printer Name type **yost2** in lower case letters. Click **Next**. You should get the message “Successfully created port yost2.” Click **OK**. Then click **Finish**. This will end the Program Setup.
17. Now go to **Start/Settings/Printers**.
18. **Select** the one named HP 4050 N PS.
19. From the **File** menu **select** “Set as Default” if you wish to make this your default printer. If not, just continue.
20. Go to **File/Properties/Device Options** Type 12000 where it says “Available Printer Memory.”
21. In **File/Properties/Device Options** where it says “Installable options” select “Number of Printer Trays 2.” Below “Change Setting” to 3. Click **Apply**.
22. In **File/Properties/Device Options** where it says “Printer Features,” select “Collate.” Change setting to “ON.” Click **Apply**.
23. In **File/Properties/Graphics** Select “Resolution” 1200 dpi. (For some applications, this might cause a problem. If it does, reset to 600 dpi.) Click **Apply**.
24. From **File/Properties/General** click **Print Test Page**. If all went well, it should print.)

25. If the test page printed, close the Printers window. You should now be ready to print. (At the moment, I cannot “Capture a Printer Port” for this printer, but hope to have a fix soon)
26. Return the CD-Rom to Diane and sign it back ion.